
TRIM & TRIMLESS MODELS : LOG3 - R / S - T / L - NC


IMPORTANT - READ CAREFULLY BEFORE INSTALLING FIXTURE. RETAIN THESE INSTRUCTIONS FOR FUTURE REFERENCE.
THIS PRODUCT MUST BE INSTALLED IN ACCORDANCE WITH THE NATIONAL ELECTRICAL CODE AND ALL APPLICABLE LOCAL CODES, BY A PERSON FAMILIAR WITH THE CONSTRUCTION AND OPERATION OF THE PRODUCT, AND THE HAZARDS INVOLVED. PROPER GROUNDING IS REQUIRED FOR SAFETY.


NEW CONSTRUCTION WITH PLASTER FRAME INSTALLATION (NC)

- A- ENGAGE THE (4) HANGER BARS IN THE PLASTER FRAME MOUNTING SLOTS AND CONNECT THEM TOGETHER.
- B- FASTEN THE HANGER BARS TO THE CEILING BRACE WITH #8 SCREWS (**NOT INCLUDED**). THE HOUSING MUST BE FLUSH WITH THE BOTTOM OF THE CEILING BRACES.
- C-INSTALL THE DRYWALL AND DO THE CUT-OUT OPENING (SEE DIMENSIONS BELOW).

Δ








Model	Housing	Cut-out dimensions (AxB)	Ceiling thickness	Clearance
LOG3R	BI-LOG3RT-NC	Ø2 ¾" (Ø 71mm)	½" - 1" (3 - 27mm)	5½" (140mm)
	BI-LOG3RL-NC	Ø 21/8" (Ø 73mm)		8" (203mm)
LOG3S	BI-LOG3ST-NC	25/8" x 25/8" (69 x 69mm)		5½" (140mm)
	BI-LOG3SL-NC	2¾" x 2¾" (71 x 71mm)		8" (203mm)


NS-610 Last update: May 16, 2022 JP - R1




TRIM KIT INSTALLATION (NC)

- A- ROUND MODEL: BEND AND HOLD THE SPRINGS AGAINST THE TRIM KIT AND ROTATE IN THE SPECIFIED DIRECTION (SEE BELOW) WHILE PUSHING UPWARD TO INSERT THE TRIM KIT INTO THE CEILING.
 - *ONCE INSERTED, SECURE THE TRIM KIT TO THE CEILING BY SCREWING (2) #8 SCREWS (NOT INCLUDED).
- A- SQUARE MODEL: INSERT THE TRIM KIT INTO THE CEILING. TO HOLD THE KIT INSIDE THE HOUSING, SCREW THE (2) FIXATION BRACKET ADJUSTMENT SCREWS WITH A DRILL (RECOMMENDED). THE BRACKETS WILL OPEN AUTOMATICALLY WHILE SCREWING.
- B- FINISH THE ASSEMBLY BY PLASTERING, SANDING AND PAINTING.







Last update: May 16, 2022

SISTEMALUX