

MOVIT SURFACE MOUNT

MODEL : S.3000 / S.3005 / S.3050 / S.3055 / S.3070 / S.3075

IMPORTANT - READ CAREFULLY BEFORE INSTALLING FIXTURE. RETAIN THESE INSTRUCTIONS FOR FUTURE REFERENCE. THIS PRODUCT MUST BE INSTALLED IN ACCORDANCE WITH THE NATIONAL ELECTRICAL CODE AND ALL APPLICABLE LOCAL CODES, BY A PERSON FAMILIAR WITH THE CONSTRUCTION AND OPERATION OF THE PRODUCT, AND THE HAZARDS INVOLVED. PROPER GROUNDING IS REQUIRED FOR SAFETY.

⚠ DISCONNECT THE MAIN LINE BEFORE WIRING SECONDARY CONNECTORS.

INSTALLATION ON SURFACE (WALL / FLOOR) WITH 4" JUNCTION BOX - REMOTE DRIVER (REM) (24V)

- A- USING PROVIDED ALLEN KEY, LOOSEN THE SET SCREWS (X2) IN ORDER TO ROTATE THE FIXTURE HEAD.
- B- PASS CABLE THROUGH CENTER HOLE OF MOUNTING PLATE, LIQUID-TIGHT CONNECTOR AND CROSSBAR, AS SHOWN BELOW. MAKE ALL NECESSARY ELECTRICAL CONNECTIONS IN THE JUNCTION BOX.
- C- INSTALL THE CROSSBAR AND THE MOUNTING PLATE ON JUNCTION BOX USING INCLUDED SCREWS, AS SHOWN BELOW.
- D- USING A FLAT-HEAD SCREWDRIVER (BY OTHERS), CAREFULLY REMOVE THE FIXTURE COVER.
- E- INSTALL THE FIXTURE ON MOUNTING PLATE USING INCLUDED MOUNTING SCREWS (X2).
- F- RE-INSTALL THE COVER.
- G- ROTATE THE FIXTURE TO THE DESIRED POSITION AND LOCK IN PLACE BY FASTENING THE SET SCREWS (2X).

A+B+C+D+E+F+G

WIRING

-	BLACK / BLUE
+	RED / WHITE

